



JA-110F Bus flood detector

The detector is used to indicate **flooding (in basements, bathrooms, etc.)**. This information is transmitted to the alarm system bus.

○ [Declaration of conformity - JA-110F \(PDF 312.95 kB\)](#)

Description

When water covers the electrodes the detector sends an activation signal, a deactivation signal is sent if the water leaves the electrodes.

It has no tamper facility and occupies one address in the system.

Technical specifications

Power	from control panel digital bus 12 V (9 ... 15 V)
Current consumption in standby mode	5 mA
Current consumption for cable selection	5 mA
Detector	reacts to flooding by water
Dimensions	53 x 20 x 10 mm
Operational environment according to	EN 50131-1 II Indoor general
Operating temperature range	-10 °C to +40 °C
Also complies with	EN 50130-4, EN 55022