



## JA-182J Wireless remote control

The JA-182J remote control is designed to **remotely arm/disarm the system, activate panic alarms and control equipment**. The key fob has a built-in convenient "child lock".

o [Declaration of conformity - JA-182J \(PDF 313.86 kB\)](#)



### Description

The "Child Lock" feature prevents the accidental activation of the unit. Pressing 2 buttons activates a panic alarm.

### Technical specifications

**Power**

lithium battery type CR 2032 (3.0 V)  
Please note: Battery is not included  
(Source type C according to EN 50131-6)

**Typical battery life**

about 4 years (5 activations/day)

**Communication band**

868.1 MHz

**Communication range**

about 30 meters (open area)

**Environment according to EN 50131-1**

II. general indoor

**Operating temperature range**

-10 °C to +40 °C

**Classification according to EN 50131-1**

Grade 2

**Can be operated to**

ERC REC 70-03

**Meets**

ETSI EN 300220, EN 50130-4, EN 55022, EN 60950-1