



## JA-187J Wireless wrist button

The JA-187J panic button can **remotely activate an emergency alarm** or **operate different devices**. It is used mainly for the **personal calling for help**.

○ [Declaration of conformity - JA-187J \(PDF 315.39 kB\)](#)



### Description

The button can be **worn like a wrist watch or around the neck** on a cord. It is powered by battery.

### Technical specifications

<b>Voltage</b>	lithium battery type CR 2032 (3.0 V/0.2 Ah)
<b>Typical battery lifetime</b>	approx. 3 years (for 1 daily activation maximum)
<b>Communication band</b>	868.1 MHz, Jablotron protocol
<b>Communication range</b>	approx. 50 m (open area)
<b>Environment</b>	external protected
<b>Housing</b>	IP-44
<b>Dimensions</b>	46 mm x 42 mm
<b>Operational temperature</b>	-25 °C to +50 °C
<b>Can be operated according to</b>	ERC REC 70-03
<b>Complies with</b>	ETSI EN 300220, EN 50130-4, EN 55022, EN 60950-1, EN 50134-2